

Technical Data

Light fitting for indoor use only

Power Factor: 1

Bulb to be used:

Nenúfar Pre-set 3A (81W)

3 x Nenúfar 3

Nenúfar Pre-set 3B (54W)

1 x Nenúfar 1

1 x Nenúfar 2

1 x Nenúfar 3

It is recommended that a professional electrician be responsible for installing the light.

Warning: *If the wire or flexible cord is damaged, it must only be changed by the manufacturer, their Service Dept. or qualified personnel in order to avoid risk.*

Cleaning Instructions

Use a soft damp cloth, with soap or neutral detergent. Do not use alcohol or other solvents.

Datos Técnicos

Luminaria para uso interior

Factor de Potencia: 1

Lámpara a utilizar:

Nenúfar Pre-set 3A (81W)

3 x Nenúfar 3

Nenúfar Pre-set 3B (54W)

1 x Nenúfar 1

1 x Nenúfar 2

1 x Nenúfar 3

Se recomienda que la instalación sea realizada por un profesional.

Aviso: Si el cable flexible o cordón de esta luminaria está dañado, deberá sustituirse exclusivamente por el fabricante o su servicio técnico o una persona de cualificación equivalente con objeto de evitar cualquier riesgo.

Instrucciones para la limpieza

Utilizar un paño suave, humedecido con agua y detergente neutro si fuera necesario. No utilizar alcohol o otros disolventes.



This symbol on the product or its packaging indicates that it must not be treated as household waste. It should, in fact, be handed in at a recognised collection point for recycling electrical and electronic equipment. For more detailed information about the recycling of this product, please contact your local city office, your household waste disposal service or the shop where you purchased the product.


Este símbolo en su equipo o embalaje indica que el presente producto no puede ser tratado como residuo doméstico normal, sino que debe entregarse en el correspondiente punto de recogida de equipos eléctricos y electrónicos. Para recibir información detallada sobre el reciclaje de este producto, por favor, contacte con su ayuntamiento, su punto de recogida más cercano o el distribuidor donde adquirió el producto.

120 V - 60 Hz

marset


NENÚFAR PRE-SET 3

Assembly Instructions / Instrucciones de montaje




marset


1.




2.1




2.2




3.1




3.2



4.



5.

**Warning!**

Disconnect power supply before installation.

Atención!

Desconectar la conexión a red antes de ser manipulada.

1. Fix the main support (A) to the ceiling using the plugs and screws provided, being sure that the hole of the main support is centered with the outlet box. Attach the electrical union (B) with the nuts (C).

2. Position and install the plate (D) using the screws (E) supplied, as shown in Figs. 2.1 and 2.2. Insert the ground wire into the connector (F).

3. Install the smaller supports (G) and attach each Nenúfar (See the Nenúfar Installation Instructions). Make sure that all the Nenúfar electrical cables are secured as shown in Fig. 3.2.

4. Make the electrical connections to the main supply. Connect the wiring for each Nenúfar to the multi-socket adaptor (I): Attach the red (or blue) wire to the positive (+ / Red) terminal and the black (or brown) wire to the negative (- / Black) terminal.

5. Attach the cover (J) by means of the screws and washers (K) provided.