

#### Datos Técnicos

Luminaria para uso interior  
Factor de Potencia: 1  
Lámpara utilizada:

88 LED 38,4W 300mA 3000K  
5600lm

Dimmer DALI / DSI

Se recomienda que la instalación sea realizada por un profesional.

**Aviso:** Si el cable flexible o cordón de esta luminaria está dañado, deberá sustituirse exclusivamente por el fabricante o su servicio técnico o una persona de cualificación equivalente con objeto de evitar cualquier riesgo.

#### Instrucciones para la limpieza

Utilizar un paño suave, humedecido con agua y detergente neutro si fuera necesario. No utilizar alcohol o otros disolventes.

#### Technical Data

Light fitting for indoor use only  
Power Factor: 1  
Bulb used:

88 LED 38,4W 300mA 3000K  
5600lm

Dimmer DALI / DSI

*A professional electrician should be responsible of the light installation.*

**Warning:** If the wire or flexible cord is damaged, it has to be changed exclusively by the manufacturer, his technical service or a qualified personnel in order to avoid any risk.

#### Cleaning Instructions

*Use a soft damp cloth, with soap or neutral detergent. Do not use alcohol or other solvents.*



Sólo aislamiento básico. Las partes accesibles están conectadas a una toma de tierra. Toma de tierra obligatoria.

*Basic insulation only! Accessible parts connected to earth lead. Apparatus must be fully earthed!*




Este símbolo en su equipo o embalaje indica que el presente producto no puede ser tratado como residuo doméstico normal, sino que debe entregarse en el correspondiente punto de recogida de equipos eléctricos y electrónicos. Para recibir información detallada sobre el reciclaje de este producto, por favor, contacte con su ayuntamiento, su punto de recogida más cercano o el distribuidor donde adquirió el producto.

*This symbol on the product or its packaging indicates that it must not be treated as household waste. It should, in fact, be handed in at a recognised collection point for recycling electrical and electronic equipment. For more detailed information about the recycling of this product, please contact your local city office, your household waste disposal service or the shop where you purchased the product.*

230 V - 50 Hz

# SOHO 57 LED

Instrucciones de Montaje / Assembly Instructions




marset




marset


1.




2.



3.



4.

**Atención!**

Desconectar la conexión a red antes de ser manipulada y realizar el cambio de bombilla sólo cuando ésta se haya enfriado.

**Warning!**

Disconnect power supply before installation and change the bulb only when cold.

1. Fijar el soporte (A) mediante los tornillos y tacos que se suministran (B), pasando los cables de red por el orificio.
2. Realizar las conexiones eléctricas: Conectar los cables N, L y en la caja de empalmes de 3 polos (C) y los cables de regulación DALI D1 (cable gris) y D2 (cable negro) en la regleta de 2 polos (D).
3. Colocar el florón (E) mediante los tornillos suministrados (F).
4. Suspender la lámpara pasando los cables de acero por los reguladores (G).

1. Fix ceiling plate (A) in position using the plugs and screws provided (B), passing the power cable through the hole.
2. Connect the wiring: Connect N, L and wires in the 3 poles' terminal strip (C) and the DALI control wires D1 (grey wire) and D2 (black wire) in the 2 poles' terminal strip (D).
3. Attach rose (E) by means of the small screws (F).
4. Hang the lamp by passing the steel wires through the slack adjusters (G).